# CAP-200 Series – Compact, 1/2"NPT Mount



- Food grade plastic housing
- No sensor well required
- ▶ Potentiometer for sensitivity adjustment

The CAP-200 Series is easily threaded directly into 1/2" NPT fittings for an easy level sensing solution within a wide variety of metal and non-metal tanks. The highly accurate sensor is built from durable Delrin® material, and is available in both aqueous and non-aqueous versions. The easy to calibrate sensor can be delivered with factory preset sensitivity for quick installation by OEM. The CAP-200 may also be used as a proximity sensor to detect the presence of solids such as paper or pulp.

### Specifications

1			
Performance	0.440" (0)		
Nominal Sensing Distance, Sn	0.118" (3mm)		
Sensing Range	0-0.118" (0-3mm)		
Repeat Accuracy - (% of Sn)	<10%		
Hysteresis - (% of Sn)	<20%		
Mechanical			
Enclosure Ratings	IP67, NEMA 1,3,4,6,13		
Operating Temperature Range	-13°F to +158°F (-25°C to +70°C)		
LED Signal Indicator	Yellow		
Power On LED Indicator	Green		
Potentiometer	Yes		
Sensor Type			
Unshielded	L-Type, Non-Embeddable		
Shielded	D-Type, Embeddable		
Barrel Material	Delrin®		
Termination	78.74" (2 meter), 3 Wire PVC		
Shock	30g, 11ms		
Vibration	55Hz, 1mm amplitude in all planes		
Max. Pressure	150 psi (10.3 bar)		
Electrical			
Supply Voltage	5-48 VDC		
Continuous Switching Current	300 mA		
Voltage Drop	<2 VDC		
Current Consumption	<10 mA		
Switching Frequency	100 Hz		
Transient Protection	2kV, 1ms, 1 k0hm		
Overload Protection	Yes		
Short Circuit	Yes		
Reverse Polarity Protection	Yes		
Approvals	CE (Except at Frequency 803-805 MHz), RoHS		

#### How To Order

Select a Part Number based on Fluid Properties and Sink State.

Fluid Properties	Container Material	Wet/Dry Sink	Part Number
Water Based, Conductive	Non-Metallic	Wet	230077
(unshielded sensor)		Dry	230078
Non-Water Based, Not Conductive	ductive Non-Metallic	Wet	230082
(shielded sensor)		Dry	230083






# **Typical Applications**

Fluid Monitoring:

- Waste
- Reagents
- Diluent
- Detergent/Wash
- Coolant
- Printing Ink

#### **Dimensions**



## Wiring Diagram

